
CMS Tracker Status, Challenges, and Performance in Run 3


Davide Zuolo - University of Colorado Boulder
On behalf of the CMS Collaboration Tracker Group





University of Colorado Boulder

Tracking detectors of CMS





• Silicon pixel tracker Barrel Pixel (BPix) and Forward Pixel (FPix)

Silicon strip tracker

Tracker Inner Barrel (TIB), Tracker Inner Disk (TID), Tracker Outer Barrel (TOB), and Tracker Endcap (TEC)

Tracking detectors of CMS






Barrel pixels (BPix) Forward pixels (FPix)


- 4 layers
 - 1184 modules 672 modules
- 4 hit coverage up to $|\eta| < 2.5$
- BPix Layer 1 replaced before the beginning of LHC Run 3


- 10 barrel layers: 4 in TIB, 6 in TOB
- 3 disks * 2 rings on each end 3 inner disk (TID) and 9 endcap disks (TEC)
 - 15148 total modules, <u>198 m² of active silicon</u>

Operational conditions in Run 3





Operational conditions in Run 3






Operational conditions in Run 3







Instantaneous luminosity was kept constant at 2.2 x 10³⁴ cm⁻²s⁻¹ for more than 7 hours → sharp pile-up profile, very high hit rate for long periods –> much more demanding environment than Run 2

Radiation status

	BPix Layer 1	BPix Layer 2-4 FPix
End of 2025 (fb ⁻¹)	320	440
End of Run 3 (fb ⁻¹)	380	500

Table 2. Expected hit rate, fluence, and radiation dose for the BPIX layers and FPIX rings [7]. The hit rate corresponds to an instantaneous luminosity of 2.0×10^{34} cm⁻² s⁻¹ [4]. The fluence and radiation dose are shown for integrated luminosities of 300 fb⁻¹ for BPIX L1 and 500 fb⁻¹ for the other BPIX layers and FPIX disks.

TDR Est	timations	Pixel hit rate [MHz/cm ²]	$\frac{\rm Fluence}{[10^{15} n_{\rm eq}/cm^2]}$	Dose [Mrad]
	BPIX L1	580	2.2	100
	BPIX L2	120	0.9	47
	BPIX L3	58	0.4	22
	BPIX L4	32	0.3	13
	FPIX inner rings	56-260	0.4-2.0	21-106
	FPIX outer rings	30-75	0.3-0.5	13-28

	Fluence [10 ¹⁵ n _{eq} /cm ²]	Dose [Mrad]
Layer 1	2.55	122
Layer 2	0.83	43
Layer 3	0.42	20
Layer 4	0.26	11
FPix - Ring 1 - low r	2.32	116
FPix - Ring 1 - mid r	0.44	23
FPix - Ring 2 - high r	0.22	12

Radiation status

BASICALLY... "THEY TRY TO BREAK US, LOOKS LIKE THEY'LL TRY AGAIN"

End of 2025 (fb ⁻¹)	320	
End of Run 3 (fb ⁻¹)	380	

Table 2. Expected hit rate, fluence, and radiation dose for the BPI The hit rate corresponds to an instantaneous luminosity of $2.0 \times 10^{\circ}$ and radiation dose are shown for integrated luminosities of 300 fb^{-1} for the other BPIX layers and FPIX disks.

TDR Estimations		Pixel hit rate	Fluence
		$[\mathrm{MHz/cm^2}]$	$[10^{15} {\rm n_{eq}/cm^2}]$
	BPIX L1	580	2.2
	BPIX L2	120	0.9
	BPIX L3	58	0.4
	BPIX L4	32	0.3
	FPIX inner rings	56-260	0.4-2.0
	FPIX outer rings	30-75	0.3 - 0.5

1	DURA	N+DL	JRAN	
n ²		thewild		

2.55	122
0.83	43
0.42	20
0.26	11
2.32	116
0.44	23
0.22	12

Silicon pixel tracker module design

Token Bit Manager (TBM)

- Controls readout of a group of 16 ROCs (module)
- Newer version in BPix Layer 1 (SEU tolerant)

High-density interconnect (HDI)


Routes high-voltage to the sensor

Planar n-in-n silicon sensor


- 285 μm thick
- 100x150 µm² pixel cells

Read out chips (ROCs)

- PROC600 >90% efficiency up to 600MHz/cm² hit rate (BPix Layer 1 only)
- PSI46dig >90% efficiency up to 200MHz/cm² hit rate (BPix Layer 2-4, FPix)





Silicon strip tracker module design




- p-in-n silicon sensors
- Two sensor thickness: 320 μm and 500 μm
- Various configurations of pitch, length, single/double sided depending on the distance from the interaction point
- Double sided modules: 2 back-to-back modules with stereo angle of 100 mrad

Detector status - Pixels BPix







Occupancy as of July 2025

Active channels: ~96%


Bml SEC7 Layers 3/4:

Fails to lock to LHC clock since the second half of 2023


Temporary and permanently disabled modules are also visible

<u>Pixels in BPix Layer 1 record more than twice as many</u> <u>hits compared to the other layers</u>

Detector status - Pixels BPix



CMS Preliminary



Occupancy as of July 2025

Active channels: ~96%


Bml SEC7 Layers 3/4:


Fails to lock to LHC clock since the second half of 2023

Temporary and permanently disabled modules are also visible

<u>Pixels in BPix Layer 1 record more than twice as many</u> <u>hits compared to the other layers</u>

Detector status - Pixels FPix






Occupancy as of July 2025


Active channels: ~94%

FPix BmO D1 ROG3:


Receives no triggers since the second half 2024

Temporary and permanently disabled modules are also visible





Detector status - Strips



Very high number of active channels: ~95% overall

Operational challenges in Run 3

Radiation effects

- Sensor degradation due to radiation damage (fluence)
 - increased leakage currents and noise
- Front-end electronics degradation due to radiation damage (dose)
- Single-event upsets (SEUs)


DRIVEN BY INTEGRATED LUMINOSITY


DRIVEN BY INSTANTANEOUS LUMINOSITY


Hardware reliability

- Connector/interconnect faults
- Auxiliary electronics failures (power/control) –> see large inactive areas in occupancy maps
- Automatic masking of problematic channels –> "The" issue since the beginning of Run 3

Radiation effects on pixel clusters







CURRENT SETTINGS:

LAYER 1: 650 V

LAYER 2: 450 V

LAYER 3: 350 V

LAYER 4: 300 V


RING 1: 450 V

RING 2: 350 V

- Layer 1 currently collecting 50% of the charge compared to unirradiated sensors –> mostly single hit clusters in X direction
- Charge collection in FPix is also degrading, but more slowly
- Improvements come from beneficial annealing, increase of HV bias, updated gain calibrations
- HV bias scan performed regularly to monitor performance

→ Layer 1 evolves rapidly


Pixel cluster breaking




- Radiation damage reduces charge collection efficiency
 - Leads to split and shortened clusters, especially in the high η region
- Consequences: more off-track clusters, increased fake/duplicate tracks, reduced resolution, especially at trigger level -> impact on physics program!
- On-track cluster size vs. η ("smiley plot"):
 - 2023: well-defined, pronounced "smiley" shape
 - 2025: more diffuse, shorter clusters especially at high $|\eta|$


A lot of efforts have been put in mitigation strategies








Auto-masked channels in pixel barrel





2023 (13.6 TeV)


-Layer 1 —Layer 2

CMS Preliminary









TBMs in Layers 2-4 get stuck following SEUs and stop sending data -> need to be powercycled in interfills

TBMs in Layer 1 (blue lines) are not affected by this issue but instead send many readout errors:

- The cause is not understood
- Auto-masking rate grows overtime
- Increasing the power to the digital electronics of the ROCs (v_{dd}) helps mitigate this

Data quality remained good for CMS

Strips depletion voltage


- Recall: strips tracker sensors are p-in-n strips
 - → depends on running over-depleted
- Depletion voltage is monitored: bias scan on full detector twice a year and on representative group once a month
- HV bias settings:
 - Baseline is 300 V
 - TEC disks 5-9 and TOB L1 and L2 increased to 500 V in July 2025
 - TEC disks 1-4 and TOB L3 and L4 also increased to 500 V in October 2025
- More frequent HV bias increases are foreseen till the end of Run 3 (June 2026)

Strips leakage current


- Leakage current per module map from 2023. Current profile is similar, except the blue-green regions are now 1000-2500 µA
- Modules in uncooled regions show large leakage current per leakage curren


1 power supply unit supplies between 2 and 12 modules


- Cooling temperature was lowered from
 -20 degC to -25 degC in June 2024
- Few HV channels per week reaching the power supply limit of 12 mA are excluded from readout



Strips signal over noise performance








- High signal to noise ratio
 - Expected to decrease with irradiation

Expected to remain sufficiently high until the end of Run 3

Hit efficiency





- High hit efficiency >98% for strips, scales linearly with instantaneous luminosity (hit rate)
- Pixels hit efficiency also shows inst. lumi (hit rate) dependence, degrades with integrated luminosity, recovered by annealing, gain calibrations, and HV bias increase

Resolution

Pixels


- Degradation overtime expected
- Worsened by cluster breaking






Strips


- Scales with pitch size
- Computed by using hits from overlapping modules






Automatic anomaly detection


- The pixel detector is prone to short (a few LS) anomalies (1 LS = 23 seconds), mainly originating from automatic recovery processes of service components
- Spotting them is not the easiest task: runs can last 100-1000 LS
- Anomalies:
 - One layer/disk: low impact on tracking
 - Overlapping layers/disks: tracking is affected → LS certified "bad"
- Improves overall data quality, minimal effect on integrated luminosity
- ML models (AutoEncoder, NMF) are being developed to aid automatization






Light ion collisions

- In July 2025, for the first time, LHC has been able to collide light (Oxygen and Neon) ions in the form of Ne-Ne, O-O, and p-O collisions
- CMS Tracker performed well during these light ions collisions





Summary and outlook

- No major failures in the last years for strips.
- Pixels lost a few components due to connector/auxiliary electronics faults
- Leakage current in strip detector is increasing but no major difference in profile compared to earlier in Run 3
- Good overall hit efficiency, resolution and signal-to-noise ratio

- Pixel Barrel Layer 1 evolves rapidly with radiation
 - Decreased charge collection efficiency
 - Cluster breaking
 - Auto-masked channels
- Tools such as automatic anomaly detection helps ensure high data quality

Pixel and Strips Tracker continue to deliver high quality tracks to CMS!!!

Summary and outlook

No major failures in the last years for Pixel Barrel Layer 1 evolves rapidly strips.

 Pixels lost a few components connector/auxiliary electroni

 Leakage current in strip dete increasing but no major diffe profile compared to earlier ir

Good overall hit efficiency, reand signal-to-noise ratio

ased charge collection ncy er breaking

masked channels

nch as automatic anomaly on helps ensure high data

Pixel and Strips Tracker continue to deliver high quality tracks to CMS!!!

References

CMS Collaboration, *Pixel Auto-masked Channels*, CMS-DP-2023-080, 2023, https://cds.cern.ch/record/2876547

CMS Collaboration, *Pixel Detector Performance in Run 3 (December 2024)*, 2025, https://cds.cern.ch/record/2923949

CMS Collaboration, CMS tracker data quality certification with new machine learning tools, 2024, https://cds.cern.ch/record/2905834

CMS Collaboration, Operation and performance of the CMS silicon strip tracker with proton-proton collisions at the CERN LHC, 2025, https://arxiv.org/abs/2506.17195

CMS Collaboration, *The CMS Phase-1 Pixel Detector Upgrade*, 2020, https://arxiv.org/abs/2012.14304

V. Chiochia et al., A double junction model of irradiated silicon pixel sensors for LHC, Nucl. Instrum. Meth. A 568 (2006) 51–55, [arXiv:physics/0506228], doi:10.1016/j.nima.2006.05.199

Backup

PSI46dig and PROC600


PSI46dig


- Used in BPix 2-4 and FPix
- Column-drain readout architecture, 160 Mb/s digital readout, enhanced charge discriminator
- >90% efficiency up to 200MHz/cm² hit rate
- Radiation tested up to 150 Mrad


PROC600


- Specifically designed for BPix Layer 1
- Faster hit transfer by grouping pixels into clusters of four for simultaneous readout
- >90% efficiency up to 600MHz/cm² hit rate
- Radiation tolerance tested up to 480 Mrad,
 with full functionality at doses up to 120 Mrad


Pixels HV bias scan

















Pixels cluster properties


- Cluster charge normalized by incidence angle
- HV: BPix L2: 350V, L3&L4: 250V, FPix R1: 400V, FPix R2: 300V








Pixel on-track cluster size


















Pixels barrel layer 1 residual offset and resolution










Detector status - Strips



Each point represents a single run

Fraction of active channels:

Global: 95%

TEC: 97%

TOB: 96%

TID: 93%

TIB: 90%

Very high number of active channels